

Number	Function
	11/30/06
F1	Test Ticket V = Changed Roll COIN RETURN = Don't Change Counters
F2	Audit Ticket Collection data form last collection to now
1	Adjust date and time.
10	Set working date
11	Select power supply.
12	Set Pay & Display machine number.
13	Adjust daylight saving changes.
14	Adjust Low ticket count alarm (green).
15	Adjust variable tariffs 6 and 7 only.
16	Adjust deferred tariff changes.
17	Adjust main board number.
18	Customise parking ticket labels (wording)
19	Print on-site programming test ticket.
21	Secret Code
23	# of spaces printed on enforcement ticket
24	Reset of CBC board
25	Machine number on DigiPark loop
26	Duplicate collection ticket.
27	Number of machines on loop (99 for stand alone) DigiPark Only
28	DigiLan Machine Status - Only prints Out of Order/Comm Problem
29	Adjust special periods.
30	Adjust holiday periods.
31	Adjust coin box level.
32	Consult variable tariffs 6 and 7.
33	Consult deferred tariff changes.
34	Print versions ticket
35	Consult holiday periods.
36	Consult special periods.
37	Adjust fines.
38	Adjust tariffs and entry times.
40	Link test modem
42	Activate general alarms
44	Vizio Phone Number (Second prompt)
47	Adjust maximum rechargeable card value.
48	Adjust door-open detection parameters.
49	Adjust coin jam detection parameters.
50	Adjust authorised/prohibited amounts.
53	Periodic settlement. (weekly or monthly)
54	Bankcard minimum payment (first push)
55	Life alarm period
56	Token alarm
57	Force exceptional CAP data transfer
64	ICS Phone Number (first prompt)
66	Redefine PBS space configuration
67	Parking Timeout
80	Initialise peripheral devices.
90	Initialise Pay & Display machine.
94	Initialise magnetic card reader.
95	Print battery voltage ticket.
96	Consult red fault LED.
97	Consult green warning LED.
98	Initialise RAM.
99	Display available programming functions.

Number	Function
100	Bill Reader Report – BNA eeprom version
101	Bill Stacker Levels Green 500, Red 700
103	Bill Channels On or Off
104	HighSecurity per bill channel
105	Bill reader calibration with special paper.
106	Bill reader test with banknotes.
107	Program level stacker jam X & Y
110	(Stelio and Strada) Coin / Bill Channels DG. Coins disable by beginning and end date. See below for instructions. Disabled coin causes all previous coins to be returned to bowl
111	Position selector wheel for replacement (Stelio only).
113	Self test (Stelio and Strada only).
114	E-lock Menu #9 = Collection Programming Anti Neutralization = ON Take key back early Transfer = OFF Not available yet
115	(DG only). Coin / Bill Channels DG. Coins disable by beginning and end date. See below for instructions. Disabled coin causes all previous coins to be returned to bowl
Functions 110 & 115 Instructions	There is only one Date Field, not two. 1: < 2: > Selecting 1 and changing the date means that channel will be enabled UP to the entered date, and disabled after that date. Choosing 2 and changing the date means that channel will be disabled UP to the entered date, enabled after that date. It is NOT a beginning and ending date range. You can only activate a 1 or a 2, NOT both.
116	Strada V-lock Lock and Unlock menu
120	Initialize BNA (Mars Only)
211	Test ticket
212	Strada Audit Ticket
350	PBS Mode
351	View PBS Lot definition
352	Print PBS local transactions
353	Send PBS local transactions
354	PBS Link test to e-ticket server
355	Delete local transactions
356	Request PBS config from Server
357	
390	Print or Program 1) Server/Client 2) Stand Alone s=page up Z=page down
391	Prints IP address' in EPROM (Server only)
392	Send test signal to Server (client only)
393	Display machine's IP address

Number	Function
500	Credit Call Telephone Number
501	Credit Call Terminal ID
502	Credit Call server link test
503	Bank On Line Maintenance
504	Program Date Maintenance
505	Epsum Phone Number
506	Wake up delay modem (GPRS)
530	Credit Call signal strength
602	RSSI Reading RF Level
604	Select RAM tariff or EPROM tariff
617	SMS Config ??????
618	????????????
890	Strada RAM Reset
900	????????????????
914	????????????????
921	RSSI Reading RF Level
930	Strada – Download drivers - yes to all Not Necessary = OK Not Compatible = Send to France mark "Boot Loader missing"
990	Print versions ticket and list of alarms