



Flowbird CWT PM Checklist  
Updated 6/30/2020

Date: \_\_\_\_\_ Terminal ID: \_\_\_\_\_ Hrs/Op/Time Limits/Rates: \_\_\_\_\_

#### GENERAL

- Check operations of coin, credit card
- Verify accuracy of time on clock display
- Open upper cabinet door, then switch main power off

#### BATTERY

- Battery Inspect main battery for signs of leakage or corrosion<sup>1</sup>
- Check battery connections
- Test and record battery voltage with voltmeter
- Voltage:

#### MAINBOARD

- Verify that the SODIMM and the SD card are seated properly

#### PRINTER-MAIN ASSEMBLY

- Printer - Main Assembly Remove dust and paper debris using soft brush and canned air

#### COIN HANDLING SYSTEM

- System Remove dust from antipin coin channels with soft brush or canned air
- Clean & apply Rain-X to coin verifier's coin-roll surfaces

#### MAG STRIPE CARD READER

- Remove dust and debris with canned air from card and head areas
- Clean head with alcohol, use new dual-reader smart-cleaning card

#### MISCELLANEOUS

- Spray all cables with Contact cleaner
- Apply Dielectric Grease to all electronic connections
- Clean inside of display window with alcohol
- Check the functionality of the doors & the tightness of the Locking assembly
- Check all hardware, cables, connectors and SD card for fit and tightness
- Check for damaged door seals Check all buttons for smooth operation
- Clean solar panel, clean exterior of cabinet and graffiti
- Check for correct placement of all stickers on door, headband and Parking P
- Check for tightness of the antenna and the solar panel Check Connection, Power Meter ON Retest coin, cc, and all button operations